

# Show File Handling

#### The Show File

The show file contains all the information that is related to the show including:

- Patch
- Fixture profiles
- Cues
- Timings
- 3D information
- Users and user profiles



Save the old show before loading or renaming a new one, to keep changes.

A show file software version can only be moved forward. A show saved on a USB stick that was programmed in a previous version can be loaded in a newer version. If the show is then re-saved on the stick in this new version, it cannot be taken back to the old software. If this is important, then it is needed to load the show and save it with a new name. Then the old version is not saved as the new version and it can still be accessed by an older version.

#### 🔄 Hint:

To learn more about the folder structure of shows, demo shows, and backups read the topics <u>File</u> <u>Management</u> and <u>Folder Structure</u>.

All the management of the show files is handled in the Backup menu.

- To access the Backup menu, press Menu .
- Tap Backup .



#### The Backup menu is open.

?					Patch	Live Patch	Output Configuration	Desk Lights Color Theme			Delete This Screen	s 3D
					Network	in & Out	DMX Protocols	Settings			Delete All Screens Configure Display	6 Help
At					Backup	Quick Save	Import / Export	Preferences and Timing			Set Dialogs to This Display Set Dialog Positions to Default	8
< □	MA	Vdmin(Fixture)>									a 📟 🙂	■ ►
Sync		Dimmer	Position	°	Color	Beam	Focus	Control	Pha	MAtricks	Prog Time Exec Time	Grand Master
	-		Sector of	1		0 0	0 0 0	0 0	•			100%
Single				Absolute	Delative Eads	Delau Coast	d Dhaca Massura	Accel Decel 1	Transition Wid	the GridDoe	4 1/1 - 10	100000000000

#### Backup menu

Or use the Menu command, to call the Backup Menu.

# Important: A loaded show file is limited to use 10 GB of memory.

#### Important:

The size of all media pools in total, is limited to a maximum of 200 MB.



#### Important:

The show file name is limited to a maximum of 31 characters.

#### Important:

The show file name must not contain the following characters: \ " \$ \* ? ^ | / : < > `

To learn more about where to see the current occupation of memory, read the **System Information** topic.



# Load a Show File

To load a show file:

- 1. Open the Backup menu and tap Load .
- 2. Select a show file and tap Load .

To load a show by the command line, use the LoadShow keyword.

# Backups and Demo Shows

To load a backup file or the demo show file:

- 1. Open the Backup Menu and tap Load .
- 2. Tap Shows to toggle between Shows , Backups , and Demo Shows .

Here it is possible to load a previously saved backup or a demo show. It is not possible to save or create a new show file in the backup or demo show folder.

It is possible to store 10 backup files from the same show file. A backup is automatically generated when saving a show file.

A backup file contains:

- Showfile Name
- Backup
- Date and Time in UTC format

٥	🔂 Backup				Backups	Internal	۵	×
*	🗲 Back	A Type to search	Clear		Fre	e Space: 80% (372	GB)	
	Date	Name	Description	Size				
	12.09.2022 15:30	Demoshow_grandMA3.backup_2022.09.12_15.30.06UTC.show		377.0 kB				
111	09.09.2022 09:42	Demoshow_grandMA3.backup_2022.09.09_09.42.05UTC.show		370.1 kB				
	09.09.2022.09:41	Demoshow_grandMA3.backup_2022.09.09_09.41.43UTC.show		370.1 kB				
Ba	ckup Files							



### Select the Drive

The show files are stored on the internal drive or a USB stick. The internal drive is Drive 1 and the USB stick is Drive 2. If more than one USB stick is connected the order of the connection selects the drive number. That means that the latest connected drive has the highest number.



The order of connecting the USB drives to the console / onPC station determines the order of the drive numbers.

In the upper right corner of the Backup menu, it is possible to select the drive you are working on. To select the drive:

- 1. Tap Internal and it toggles between the different drives connected or shows saved in older software versions.
- 2. Tap and swipe right on the drive and a pop-up opens with the different opportunities.

The drive can also be selected by the command line.



The backup menu displays the free disk space of the selected drive in the upper right corner of the menu:



Showing free disk space in percent and gigabyte

# Quick Save

To save the show file quickly:

- Press Menu and tap Quick Save
- Pressing quickly 2 x Menu also makes a Quick Save.



# Auto Save

To save the show automatically in regular intervals, activate the Auto Save function. Tap Backup and

AutoSave Interval

Φ	1	Backup															Inte	rnal	۵	×
*		Current Show														Free Sg	bace: 8	0% (3754	3B)	
*		Description																		
1t1																			-	
:11																				
				1										_						
_				-		Lord			D.		Mauri	Chana								
ų.						Load					New :	SHOW								
?																				
				•		Save As					Save	e To mai								
				45 1944 (*					1											
				B		Delete														
				4					ļ											
Ŧ		AutoSave Interval	Funant Madia	Farmerate Ch.																
Ľ		off	on Show Save	when Descript	ion Changes														_	
•	MA	Admin(Fixture	e)>													ക		58 (	900	. ►
S	me	Dimmer	Position		Color		Bea	m		Focus		Cont	rol	Phaser	MAtricks	Prog	Time	Exec Tin	ne N	irand faster
Sin	igle ep	Dimmer 1 of 1	Link Values Single	Absolute	Relative	Fade	Delay	Speed	Phase	Measure	Accel	Decel	Transition	Width	GridPos	<b>+</b> 1	/1	÷ k	2	100%
Align		Dim	Dim																	
Read	tut		94												ŏ	Screen				
Nat	lural																		-	

Auto Save Interval

Select the desired Auto Save interval.

Select AutosaveInterval 💥
Off
5 Minutes
15 Minutes
30 Minutes
60 Minutes
120 Minutes
360 Minutes

Select Auto Save



### Save Show As

To save a show with another name, open the Backup Menu and tap Save As .Write the new name of the show file in the Name field. Tap Save as... and confirm pop-up window with Ok . The show file is saved by its new name.

To save a show by the command line, use the **SaveShow keyword**.

# Save To Internal

To select and change the internal/external drive to save a show file on:

- 1. Tap Internal in the top right corner in the Backup Menu.
- 2. The name of Save To Internal button will automatically adjust to the name of the drive.
- 3. Tap Save To <Name of Drive> to save the show on the selected drive.

				Internal Removab D:\	Internal ce: 81% (379G	≏ 🕽
2	Load	D	New Show			
	Save As		Save To Internal			
ß	Delete					

Save a show on an internal selected drive



# Add a Description

To add a describtion to the show file at the top of the backup menu, an area allows you to enter and read the description of the loaded show file. Modifying or entering a description will only be applied to the show file when saving it afterwards.

٢	1	Backup															Inte	ernal		×
**		Current Show														Free S	pace: 8	30% (3)	SGB)	
*		Description																		
		1																		
111																			5	
:11																				
				0					_											
				-		Load	1		D		New S	Show								
- 2								1												
				12 11 - 11 - 11 - 11 - 11 - 11 - 11 - 11																
						Save	As				Save	e To mai								
									÷											
				гъ		Delet														
-				LA																
At																				
۲		AutoSave Interval Off	Export Media on Show Save	Enumerate Sho when Descripti	w File Nam ion Changes	e														
•	MA	Admin(Fixture	Þ																	
Sy	nc													Phaser	Mitricks	Prog	Time	Exec	Time	Grand Master
Sin	igle ep		Link Values Single	Absolute	Relative	Fade	Delay	Speed	Phase	Measure	Accel	Decel	Transition	Width	GridPos	+	1	+	:0	100%
Align																Screet	۱Y			
Reads	tut														ě.	Screet				
Nat	lural																			

To add another line, press Enter .

Show file name with description line



#### Show File History

To have a look at the show file history:

- 1. Tap Load in the backup menu. Enable Show History in the bottom left corner.
- 2. The history of the selected show file is displayed at the bottom of the backup menu.

When loading the show file, the history gives information regarding:

- Dates, time and timezone
- Used software version
- Software type
- Name

A new entry within the history will be entered, when the show file will be saved again and one of these criteria has changed:

- Version
- Туре
- Name
- Time zone
- Description

The newest entry is on top of the history list.



٩	Backup	Q								-	Clear					Shows	Free S	Inte pace: 8	ernal 30% (37	5GB)	• *
*	Date	<u> </u>		Name				Descriptio	n		Size										
Ω	30.08.2022 11:44	NewSi	how_MA_S	TART.show				Description	11		121.3 kB										
1+1	30.08.2022 11:42	2 NewSi	how.show				R	scription Li	ine 1		122.0 kB										
+1+								scription c	BPC 2												
:11																					
÷																					
?																					
	Date	Ve	ersion	Туре	Na	ame		Descr	iption			UTC									
-	30.08.2022 11:4	4 1.	8.1.0	Release	NewShow,	MA_START		Descri	ption 1		2	30.08.2022	9:44								
At	30.08.2022 11:4		8.1.0	Release	NewShow,	MA_START						30.08.2022	19:43								
T	Show		Show	~																	
	History	De	scription																6	, L	oad
•	MA 📼 Adr	nin(Fixture	÷																		BOAR >
Sy	nc														Phaser	MAtricks	Prog	Time	Exec T	Time	Grand Master
Sin	ale		Link Value	6	Absolute	Delation	Endo	Delay	Coasd	Dhare	Manager	Accel	Decel	Transition	Width	Oridina			-		100%
St	ép			Single	Absolute	Relative	Fade	Delay	speed	Phase	measure	Accel	Decei	Transition	width	GndPos	-		7	:0	
Alagan O	er																				
Reado	* tut																				
Nat	ural															•					

Show file name with description and time stamp



#### Add Automatic Numbering

It is possible to add 3-digit numbers to the show file name.

In order to separate the show file name from the number, the user can add a hyphen (-) or an underscore (\_) or any other character to separate the name from the numbers at the end of the show file name.

The option Enumerate Show File Name when Description Changes in the Backup Menu provides an automatic increase of a 3-digit number, added to the end of the show file name if the description is changed when saving the show.

Φ	🐏 Backup															Inte	ernal	-	*
	Current Show		1												Free	Space: I	30% (37	5GB)	
*	Description																		
	Description 1 Description 2																		
111	Description 3																		-
:11																			
			-		Load			n		New S	show								
-																			
1			93. 																
					Save /	As .				Save	e To mai								
			_																
			_																
-			LX		Delet	e													
At																			
Ŧ	AutoSave Interval	Export Media	Enumerate Sho	w File Name	2														
	MIA E Adminiferture	off allow save	when bescripti	on changes											Å				
														Mitricks	-			-	Grand
Syr	nc												Phaser		Pro	g Time	Exec T	ime	Master 100%
Sin	gle ep	Single	Absolute	Relative	Fade	Delay	Speed	Phase	Measure	Accel	Decel	Transition	Width	GridPos	+	1	+ :	0	
Align Of	н																		
Reado														0					

Show File name with automatic numbering

If the original show file name is too long to add the number, the command line will return an error. In this case, the former show file name will be used again.

Enumerating a show file can also be called with the /Enumerate option.

For more information see /Enumerate option keyword.



#### New Show

- To create a new empty show file, open the Backup Menu and tap <u>New Show</u>. A popup window appears. A automized file name is created like New Show-date-time.
- Leave or rename the file name for the new show in the Name field. When the name is correct, tap Enter .
- Create New Show popup window appears, tap New Show .

To create a new show by the command line, use the LoadShow keyword.

**Hint:** It is possible to use local letters in the filename, like æ, õ, and ä.

# Delete a Show File

Open the Backup Menu and tap Delete . Tap the show file to delete. Tap Delete in the bottom right corner and the show file is deleted.

#### Load a Show File During Startup

It is possible to specify a show file or a plugin that shall be loaded upon starting the onPC application.

To do so, add the SHOW or RUNPLUGIN parameter to the shortcut that launches the onPC application:

- "C:\Program Files\MALightingTechnology\gma3\_x.x.x\bin\app\_system.exe" HOSTTYPE=onPC SHOW="startshow.show"
- "C:\Program Files\MALightingTechnology\gma3\_x.x.x\bin\app\_system.exe" HOSTTYPE=onPC RUNPLUGIN="startplugin.xml"-x
  - x represents the number of the LUA component inside the plugin, that shall be started, e.g., 1
  - It is not recommend to specify a path for the plugin although the plugin may be put into a subfolder.

Replace "x.x.x" with the grandMA3 onPC version number.

In addition, the optional parameters NOLOAD and CLEANSTART are also available when starting onPC.

- NOLOAD will not load the last show file but start with an empty show. Other device related configurations are kept.
- CLEANSTART will reset device related configuration back to default and come up with an empty show file.



Do not use spaces in a show file name when loading a show during the startup process.

Hint: Repla



Terminal C	ompatibility Secur	ity Detail	Previou	ue Vereione										
General Sh	ortcut Options	Font	Layout	Colors										
MA gra	andMA3 onPC													
Target type:	Application													
Target location: bin Target: <a href="https://www.show">www.show</a> Target: <a <="" a="" href="https://www.show"></a>														
Target: <a href="https://www.show">www.show</a> Start in: <a href="https://www.show">www.show"</a>														
Start in:	"C:\Program Files\M	1ALighting Te	chnology\gm	a3_										
Shortcut key: None														
Shortcut key:     None       Run:     Normal window														
Comment:	MALightingTechnolo	ogy - grandM	A3 on PC											
Open File Lo	ocation Change	Icon	Advanced.											

Windows 11 properties are shown as an example for the load show process.



# Export Media on Show Save

In order to save media files (e.g. images, videos, etc.) to the **gma3\_library folder**, activate the Export Media on Show Save function. Tap Backup and Export Media on Show Save .

٢	B.	Backup															Int	ernal		•	×
*		Current Show NewShow_2 Description	2022.08.30_11.5	8.10UT	ſĊ											Free	Space:	80% (3	74GB)		
																				-	
:IT 									i i												
<b>P</b>				-		Load			D		New S	how									
?				а. С				-	1												
						Save	As				Save Inter	To nal									
				₿		Delet															
At <b>T</b>		AutoSave Interval Off	Export Media on Show Save wi	umerate Sho hen Descript	w File Nam ion Changes	e															
•	MA	Admin(Fixture	₽													da		8	•	510.01	۲
Sy	nc													Phaser	MAtricks "	Prog	Time	Exec	Time	Gra Mat	nd iter
Sin St	gle ep	l l	Link Values Single	Absolute	Relative	Fade	Delay	Speed	Phase	Measure	Accel	Decel	Transition	Width	GridPos	+	1	+	ю		
Align O	ff														۲						
Reads Nat	ut ural														0						

A show file with Export Media on Show Save