

+ [Plus] Command

This page describes the syntax and how to use the + [Plus] command.

Description

With the + [Plus] command you can:

- Add objects to a selection list
- Add the dimmer value
- Call the next page

Syntax

1. Add objects from a list:

A dark grey rectangular box representing a command input field. On the left, the text '+ 5' is displayed in white. On the right side, there is a small, faint icon consisting of a grid of dots with a horizontal line below it.

+ 5

2. Add dimmer values:

A dark grey rectangular box representing a command input field. On the left, the text 'At + 12' is displayed in white. On the right side, there is a small, faint icon consisting of a grid of dots with a horizontal line below it.

At + 12

3. Call next page:

A dark grey rectangular box representing a command input field. On the left, the text 'Page +' is displayed in white. On the right side, there is a small, faint icon consisting of a grid of dots with a horizontal line below it.

Page +

The + [Plus] command is a helping command and needs a further command or a number.

Example 1

Let's assume, you have a long selection list with fixtures and you will add one to them.



ID	Name
1	QWO 1
2	QWO 2
3	QWO 3
4	QWO 4
5	QWO 5
6	QWO 6
7	QWO 7
8	QWO 8

Figure 1: Fixture selection list - one fixture is missing

- Press **+** **5** **Please** on the console.

The fixture ID 5 is added to the selection list.

ID	Name
1	QWO 1
2	QWO 2
3	QWO 3
4	QWO 4
5	QWO 5
6	QWO 6
7	QWO 7
8	QWO 8

Figure 2: Complete fixtures selection list

Example 2

Let’s assume, you have a long selection list with fixtures and you will add fixture ID 5 thru 7.



ID	Name
1	QWO 1
2	QWO 2
3	QWO 3
4	QWO 4
5	QWO 5
6	QWO 6
7	QWO 7
8	QWO 8

Figure 3: Fixture selection list - fixture 5 thru 7 are missing

- Press **+** **5** **Thru** **7** **Please** on the console.

The fixture IDs 5 thru 7 are added to the selection list.

ID	Name
1	QWO 1
2	QWO 2
3	QWO 3
4	QWO 4
5	QWO 5
6	QWO 6
7	QWO 7
8	QWO 8

Figure 4: Complete fixture selection list

Example 3

Let’s assume, you will add the dimmer value by 12% from selected fixtures.

ID	Name	Dim
1	QWO 1	38.0
2	QWO 2	38.0

Figure 5: Dimmer at 38%



- Press **At** **+** **12** **Please** on the console.

The dimmer values are added by 12%.

ID	Name	Dim
1	 QWO 1	50.0
2	 QWO 2	50.0

Figure 6: Dimmer at 50%



Hint:
To add the dimmer value by 10%, press the **+** key twice.

Example 4

Let's assume, you will call the next page.

- Press **Page** **+** **Please** on the console.

The next page opens.